

# ATS1140

## 7" touchscreen for Advisor Advanced

### At a glance

---

The Advisor Advanced product family has a new addition: the ATS1140 graphical touchscreen. This device offers simple fingertip control of the security system with a 7-inch high-responsive touchscreen display that features easy-to-understand graphics. The ATS1140 is designed to perfectly complement other control units in the Advisor Advance security system family, ensuring a smooth user experience.

The ATS1140 boasts a modern design with a new graphical user interface that features icon-based and readable text. The display's contrast and the built-in buzzer's volume level can be adjusted via the configuration board. This device also comes with a simplified and intuitive graphical user interface, allowing users to easily navigate the programming, operational features, dashboard, system status, alarms, logs, and additional function keys.

Overall, the ATS1140 graphical touchscreen combines functionality and style to provide an efficient and user-friendly experience.

### Built-in secure card reader

---

The ATS1140 is equipped with a Mifare Desfire EV1/EV2/EV3 card reader that is built-in. When the device is in secure mode, the data is encrypted from the card to the keypad and from the keypad to the Advisor Advanced control panel.

The ATS1140 can be used for arming/disarming the system with the PIN code, the card or a combination of both for enhanced security. It works with the multiple card badging solutions that are available in the Advisor Advanced product family.

Alarm system activation: a user can turn on the alarm system by badging their card three times within a 10-second interval.

Door access control: doors can be programmed for specific behaviors based on badging with the card. For example, with a single badge scan, granting seamless entry and exit without requiring a card, and a triple badge scan will promptly re-lock the door, providing enhanced convenience for the end user.

### Quick access

---

The touch display menus are thoughtfully organized, featuring a clean and intuitive design that makes navigation a breeze. The single-touch operation eliminates the need for complex maneuvers, allowing for effortless interaction with the system. Whether you are an advanced tech user or a novice, you will find the touch display menus to be user-friendly and highly accessible.

### Quick and easy installation

---

Screw the back plate onto the wall, connect the data bus cable from the panel, snap the touchscreen onto the plate: you're all set up and ready to go.



### Details

---

- Streamlined, modern design
- Simplified and intuitive graphical user interface
- 7" colour touchscreen
- Possibility to add a customized logo on the display
- Quickly accessible and programmable function keys
- Built-in secure Mifare Desfire EV1/EV2/EV3 reader
- User-adjustable LCD, buzzer and key lights
- Use secure ATS145x series cards or custom cards (excl. ATS1458)
- Intuitive and simplified icon-based user interface
- Multi-language support
- Virtual keypad

This installation method is not only easy to follow, but it also ensures a secure fit for your touchscreen, providing you with peace of mind knowing that your device won't fall off the wall.

In order to connect the Advisor Advance security system to ATS1140, the panel must have MR4.10 or later. Please contact your local support for assistance if needed.

# ATS1140

## 7" touchscreen for Advisor Advanced

### Technische specificaties

#### Systeem

|                       |                          |
|-----------------------|--------------------------|
| Ondersteund kabeltype | WCAT 52/54 or equivalent |
|-----------------------|--------------------------|

#### Communicatie

|             |            |
|-------------|------------|
| Leesafstand | Up to 3 cm |
|-------------|------------|

#### Ingangen / uitgangen

|             |                      |
|-------------|----------------------|
| Ingangstype | Request to Exit (NO) |
|-------------|----------------------|

|              |                                              |
|--------------|----------------------------------------------|
| Type uitgang | Open collector (OC), 100 mA max, 15 VDC max. |
|--------------|----------------------------------------------|

#### Elektrisch

|                  |                                      |
|------------------|--------------------------------------|
| Bedrijfsspanning | 12.0 to 13.5 VDC (provided by panel) |
|------------------|--------------------------------------|

|                |                                                                                                                                               |
|----------------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| Stroomverbruik | 330 mA at 13.7 VDC, 375 mA at 12 VDC (max.)<br>220 mA at 13.7 VDC, 250 mA at 12 VDC (average)<br>70 mA at 13.7 VDC, 80 mA at 12 VDC (standby) |
|----------------|-----------------------------------------------------------------------------------------------------------------------------------------------|

#### Fysiek

|                    |                   |
|--------------------|-------------------|
| Fysieke afmetingen | 127 x 179 x 20 mm |
|--------------------|-------------------|

|               |       |
|---------------|-------|
| Netto gewicht | 460 g |
|---------------|-------|

#### Omgeving

|                     |            |
|---------------------|------------|
| Bedrijfstemperatuur | 0 to +50°C |
|---------------------|------------|

|                       |                         |
|-----------------------|-------------------------|
| Relatieve vochtigheid | up to 95% noncondensing |
|-----------------------|-------------------------|

|                  |              |
|------------------|--------------|
| IP-classificatie | IP30<br>IK06 |
|------------------|--------------|

#### General

|          |                        |
|----------|------------------------|
| Language | Multi-language support |
|----------|------------------------|

|                    |                 |
|--------------------|-----------------|
| Supported Firmware | MR4.10 or later |
|--------------------|-----------------|

#### Communication

|        |                    |
|--------|--------------------|
| Wiring | RS-485, 4-wire bus |
|--------|--------------------|

|                        |                                  |
|------------------------|----------------------------------|
| Connected per data bus | 8 per data bus max 16 per system |
|------------------------|----------------------------------|



Als een bedrijf van innovatie behoudt Carrier Fire & Security zich het recht voor productspecificaties zonder kennisgeving te wijzigen. Ga voor de nieuwste productspecificaties online naar [nl.firesecurityproducts.com](http://nl.firesecurityproducts.com) of neem contact op met uw verkoopvertegenwoordiger.

Last updated on 10 April 2024 - 14:51